



Please carefully read before use:

Installation and Operation Instructions:

1. Place ring light on the pot rim, or directly on the soil or other grow media surface. Direct pesticidal light upward through the canopy.
2. Connect pesticidal ring light to a waterproof timer capable of one-minute increments.
3. Ensure the timer is set to provide only 1-15 minutes of light every 24, during the dark period, ideally 4 hours into the dark period, with 4 hours of darkness remaining after the treatment.
4. Ensure NO workers are present during the light exposure period.
5. Connect the timer to a waterproof GFCI outlet.
6. Up to 80pcs ring lights CAN be daisy chained together if the resulting power draw does not overload the connected outlet/timer. Ensure all daisy-chain connections are fully connected and secure.

⚠ Caution, Important safety information:

- Photo-period sensitive crops will not have their photoperiod effected by the nightly light treatment.
- Exposure to the pesticidal ring light spectrum may be harmful. DO NOT operate while persons are present in the grow area. LEDINPRO is not responsible for human exposure resulting from improper use.
- Regulating timers should be checked regularly to ensure no accidental pesticidal light exposure.
- If signs of phytotoxicity occur when testing ring light on specific crops and cultivars, stop use immediately. LEDINPRO will not be responsible for damage to crops resulting from failure to follow proper testing procedures.
- If a cable becomes frayed, cracked, or damaged in any way stop using immediately.
- When connecting multiple ring lights together in a daisy chain, ensure all connections are tight and completely connected. Failure to do so may result in electric shock and injury.
- End cap must be used on last light to ensure waterproof.
- Attempting to open and/or repair the device can present the risk of electric shock, device damage, fire, personal injury, and other hazards. Do not attempt to open and/or repair the device. Contact LEDINPRO offices for repairs and replacements.
- The warranty is void if the device user disassembles, tampers with or damages products or labels. LEDINPRO will not be responsible for any damage to the device resulting from unauthorized modifications or repairs.